

Maxwellian fields for a ring derived from multipole end fields

S. Brooks

November 2024

Collider Accelerator Department
Brookhaven National Laboratory

U.S. Department of Energy
USDOE Office of Science (SC), Nuclear Physics (NP)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No. DE-SC0012704 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Maxwellian Fields for a Ring derived from Multipole End Fields

Stephen Brooks

November 12, 2024

1 Turning an End Field on its Side

A previous note derived the following expression for a magnetic field that is order n rotationally symmetric about the z axis:

$$\mathbf{B} = \sum_{j=0}^{\infty} C_{nj} r^{n+2j-1} \begin{bmatrix} ((n+j) \sin((n-1)\theta + \psi) + j \sin((n+1)\theta + \psi)) f^{(2j)}(z) \\ ((n+j) \cos((n-1)\theta + \psi) - j \cos((n+1)\theta + \psi)) f^{(2j)}(z) \\ r \sin(n\theta + \psi) f^{(2j+1)}(z) \end{bmatrix}.$$

Here, $r = \sqrt{x^2 + y^2}$,

$$C_{nj} = \prod_{i=1}^j \frac{-1}{(n+2i)^2 - n^2} = \prod_{i=1}^j \frac{-1}{4(n+i)i} = \frac{(-\frac{1}{4})^j n!}{(n+j)! j!}$$

and $f(z)$ is proportional to the strength variation of the $2n$ -pole along the z axis. $\psi = 0$ gives normal orientation and $\psi = \frac{\pi}{2}$ the skew orientation.

The idea of this note is to reinterpret (x, y) as the plane of a ring with superperiodicity n , making z the ‘vertical’ or out-of-plane axis. The vertical B_z component is oscillatory but can be supplemented by a constant field in that direction, producing something similar to ‘field flutter’ in cyclotrons, including the alternating gradients that keep the beam stable. Normally it is desired that the $z = 0$ ring plane only has field perpendicular to it, meaning $B_x = B_y = 0$ there. This can be guaranteed by making $f(z)$ an odd function, so that $f^{(2j)}(0) = 0$ for all j .

2 f with Order 1

The simplest case with $f(z)$ an odd polynomial is $f(z) = az$. As f'' and all higher derivatives are zero, only the $j = 0$ term is nonzero. Note that $C_{n0} = 1$ and then

$$\mathbf{B} = r^{n-1} \begin{bmatrix} n \sin((n-1)\theta + \psi) az \\ n \cos((n-1)\theta + \psi) az \\ r \sin(n\theta + \psi) a \end{bmatrix}.$$

The peak strength of the dipole field on the midplane is ar^n and the peak gradient is anr^{n-1} .

This field model has the advantage of being very simple. It is also the field of a scaling FFA with field index $k = n$ and a cell with sinusoidally-varying focussing (not a very efficient machine as the reverse bending nearly equals the bending). If more complex cells are desired, terms replacing n with $2n$, $3n$, etc. can add longitudinal harmonics to the periodic cell.

One disadvantage of this field model for larger beams is that it also has a sextupole $\frac{d^2 B_z}{dr^2}$ of peak strength $an(n-1)r^{n-2}$ that leads to nonlinear beam transport.

3 f with Order 3

The second simplest case is $f(z) = az + bz^3$. Now the $j = 0, 1$ terms are the only nonzero ones. $C_{n1} = \frac{-1}{4(n+1)}$ and

$$\mathbf{B} = r^{n-1} \begin{bmatrix} n \sin((n-1)\theta + \psi)(az + bz^3) \\ n \cos((n-1)\theta + \psi)(az + bz^3) \\ r \sin(n\theta + \psi)(a + 3bz^2) \end{bmatrix} \\ + \frac{-1}{4(n+1)} r^{n+1} \begin{bmatrix} ((n+1) \sin((n-1)\theta + \psi) + \sin((n+1)\theta + \psi))6bz \\ ((n+1) \cos((n-1)\theta + \psi) - \cos((n+1)\theta + \psi))6bz \\ r \sin(n\theta + \psi)6b \end{bmatrix}.$$

The peak strength of the dipole field on the midplane is now $ar^n - \frac{6b}{4(n+1)}r^{n+2}$. The peak gradient is $anr^{n-1} - \frac{3b(n+2)}{2(n+1)}r^{n+1}$ and the peak sextupole $\frac{d^2 B_z}{dr^2}$ is $an(n-1)r^{n-2} - \frac{3b(n+2)}{2}r^n$. To make the sextupole zero at radius $r = R$, it is required that

$$an(n-1) = \frac{3b(n+2)}{2}R^2 \quad \Rightarrow \quad b = \frac{2n(n-1)}{3(n+2)R^2}a.$$

This makes the peak dipole field at radius $r = R$ equal to

$$aR^n - \frac{6}{4(n+1)} \frac{2n(n-1)}{3(n+2)R^2} aR^{n+2} = \left(1 - \frac{n(n-1)}{(n+1)(n+2)}\right) aR^n$$

and the peak gradient at $r = R$ equal to

$$anR^{n-1} - \frac{3(n+2)}{2(n+1)} \frac{2n(n-1)}{3(n+2)R^2} aR^{n+1} = \left(1 - \frac{n-1}{n+1}\right) anR^{n-1}.$$

4 General Case

Higher order polynomials may be useful for cancelling octupole and higher nonlinearities. For odd $f(z)$, the field on the midplane is

$$B_z(z=0) = \sum_{j=0}^{\infty} C_{nj} r^{n+2j} \sin(n\theta + \psi) f^{(2j+1)}(0).$$

The peak i^{th} radial derivative field is then

$$B_{z,peak}^{(i)} = \sum_{j=0}^{\infty} C_{nj} \frac{(n+2j)!}{(n+2j-i)!} r^{n+2j-i} f^{(2j+1)}(0).$$

If $f(z) = \sum_{k=0}^K a_{2k+1} z^{2k+1}$ then $f^{(2j+1)}(0) = (2j+1)! a_{2j+1}$ for $j \leq K$ and zero otherwise, giving

$$B_{z,peak}^{(i)} = \sum_{j=0}^K C_{nj} \frac{(n+2j)!}{(n+2j-i)!} r^{n+2j-i} (2j+1)! a_{2j+1}.$$

Typically a radius $r = R$ will be chosen at which several ($K + 1$) of the $B_{z,peak}^{(i)}$ are specified (e.g. nonzero gradient $i = 1$, some higher multipoles zero). The values of $R^n a_{2j+1}$ can be obtained by solving the linear system

$$B_{z,peak}^{(i)} = \sum_{j=0}^K \frac{(-\frac{1}{4})^j n!}{(n+j)! j!} \frac{(n+2j)!}{(n+2j-i)!} R^{2j-i} (2j+1)! (R^n a_{2j+1}).$$

The factor R^n can be too large for the computer precision, so is included in the coefficient value. The field can then be calculated with the rescaled formula

$$\mathbf{B} = \left(\frac{r}{R}\right)^n \sum_{j=0}^{\infty} C_{nj} r^{2j-1} \begin{bmatrix} ((n+j) \sin((n-1)\theta + \psi) + j \sin((n+1)\theta + \psi)) R^n f^{(2j)}(z) \\ ((n+j) \cos((n-1)\theta + \psi) - j \cos((n+1)\theta + \psi)) R^n f^{(2j)}(z) \\ r \sin(n\theta + \psi) R^n f^{(2j+1)}(z) \end{bmatrix}.$$