



BNL-103963-2014-TECH

AGS.SN85;BNL-103963-2014-IR

## Linac beam bunching at 2.5 MHz (ring rf frequency)

N. Fewell

April 1977

Collider Accelerator Department  
**Brookhaven National Laboratory**

**U.S. Department of Energy**

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.EY-76-C-02-0016 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

## **DISCLAIMER**

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Date 4/21/77 Time 1800-2100 Experimenters N. Fewell

Subject Linac beam bunching at 2.5 MHz (ring rf frequency)

OBSERVATIONS AND CONCLUSION

Setup - The linac buncher #1 was run at 2.5 MHz higher in frequency than the linac tanks, this causes the bunched beam to move across the phase acceptance of tank #1, producing an amplitude modulated beam at 2.5 MHz.

Procedure - As the present buncher tuning range is only  $\pm 500$  KHz about the linac frequency (201.25 MHz) the effective length of buncher #1 had to be shortened. This was accomplished by changing the capacitor plates that form an rf short circuit at the ends of the buncher cavity. The buncher cavity and rf system was then tuned to 203.75 MHz using a signal generator. 3.5 mW of 2.5 MHz from the ring starting oscillator was then mixed with 40 mW from the linac reference line using a balanced mixer. The upper sideband of 203.75 MHz was then amplified to 40 mW with a Boonton amplifier and fed into the amplifier system. The Q of the cavity and amplifiers was sufficient to attenuate the carrier and lower sideband frequencies.

Results - Using buncher #1 only, at normal gradient, the beam out of tank #9 was modulated 53%.  $I_{\text{peak}} = 55$  mA,  $I_{\text{min}} = 26$  mA,  $I_{\text{ave}} = 40$  mA.

Using buncher #2 only (linac freq.)  $I_{\text{ave}} = 57$  mA.

Using both bunchers at normal settings the modulation was 39%.

$I_{\text{peak}} = 71$  mA,  $I_{\text{min}} = 43$  mA,  $I_{\text{ave}} = 57$  mA.

Comments - This method is an effective way of modulating the linac beam. No attempt was made to maximize the modulation or ring capture at this time.