



Brookhaven  
National Laboratory

BNL-103989-2014-TECH

AGS.SN111;BNL-103989-2014-IR

## Radial Control of Magnetic Field or a 6.75 GeV/c Flat Top

E. Raka

July 1978

Collider Accelerator Department  
**Brookhaven National Laboratory**

**U.S. Department of Energy**

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.EY-76-C-02-0016 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

## **DISCLAIMER**

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Date 6/20/78 Time 2200-2400 Experimenters E. Raka, E. Gill, A. FeltmanSubject Radial Control of Magnetic Field or a 6.75 GeV/c Flat TopOBSERVATIONS AND CONCLUSION

Purpose: To close a servo loop between the radial position of the beam and the flat top voltage control loop with the AGS beam frequency phase locked to an external oscillator.

Introduction: As noted in Studies Report #110, when flat topping at energies near the transition energy of  $\approx 8$  GeV the pulse to pulse variations in momentum can be as large as  $\pm .1\%$  or more. At fixed frequency this results in large ( $>1$ cm) radial position variations on the flat top. Thus it seemed reasonable to use this fluctuation to control the flat top voltage so that the final radial position would be defined by a given pick-up electrode. By fixing both frequency and position the momentum would then be reproduced with great accuracy from pulse to pulse.

Procedure: A low intensity beam ( $< 2 \times 10^{12}$ ) was used and time comb "F" was introduced to give a flat top at a  $\beta\gamma$  of  $\approx 7.19$ . Then the frequency synchronization loop was adjusted to provide a phase locked frequency of  $4,414,700 \sim$  (Gauss clock  $\approx 13,340$ ). This provided a radial offset at I-7 of  $\approx 0$  cm. It should be noted that the peak to peak radial excursions were less than half those observed on 4/13/78.

Then shortly after the frequency loop was closed the output of the I-7 radial position detector was gated into the  $\dot{B}$  servo input. This signal then is effectively added to the reference that controls the flat top voltage. The resulting loop then changes the magnet voltage and hence field. With the maximum gain available of one volt/cm from the radial detector chassis, a simple exponential response was observed when this loop was closed.

Results: The time constant of the decay was measured to be 50-55 msec for the gain mentioned above. This is a factor of two larger than calculated from a previous measurement of the gain of the  $\dot{B}$  servo loop, to a step input. The reproducibility of the final radius from pulse to pulse was better than  $\pm .5$  mm. At constant frequency and for this momentum, that corresponds to a  $\Delta B/B = -19 \Delta R/R \approx 19 \times .1 \times 10^{-3} / 12.85 \approx 1.5 \times 10^{-4}$ .

Discussion: This reproducibility along with excitation of the horizontal sextupoles to minimize the nonlinear effect at transition (see Studies Report 110), should make it possible to measure the longitudinal coupling impedance with sufficient accuracy in the region of the transition energy.

Since the response of the loop was still a simple exponential, it should be possible to decrease the time constant further by increasing the radial signal gain by up to a factor of two or more. It is planned to do this soon as well as to repeat more carefully the gain and response measurements of the flat top voltage control loop.