

BNL-105180-2014-TECH

Booster Technical Note No. 136;BNL-105180-2014-IR

MAGNET WAVE PROPAGATION

M. Meth

January 1989

Collider Accelerator Department Brookhaven National Laboratory

U.S. Department of Energy

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.DE-AC02-76CH00016 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

MAGNET WAVE PROPAGATION

AD BOOSTER TECHNICAL NOTE NO. 136

M. METH

JANUARY 30, 1989

ACCELERATOR DEVELOPMENT DEPARTMENT BROOKHAVEN NATIONAL LABORATORY UPTON, NEW YORK 11973

MAGNET WAVE PROPAGATION

M. METH January 30, 1989

INTRODUCTION

The application of a voltage pulse to the AGS Booster magnet string produces an initial transient response that is characterized as a wave. The wave response results from the distributed inductance and capacitance of each magnet around the ring structure and is similar to the response of a short-circuited transmission line. The wiring of the dipole magnet string is shown in Figure 1. The wave propagates within the magnet string and results in magnetic fields that vary with position around the ring structure. The wave is damped by losses associated with the iron laminations, coil winding and by an external resistor shunted across each half coil of the magnet structure. Following the damping of the wave, the magnet string behaves as a lumped-constant inductor and the magnetic field is uniform around the ring structure.

Model of Magnet

The electrical model of the dipole magnet is highly frequency dependent and consists of a series inductor and resistor and a shunt capacitor. The frequency dependence of the model is due to flux shielding by the iron, with the value of the series inductor varying from that of an iron-core (low frequency value) to an air-core (high frequency value) with an equivalent winding configuration.

The wave response is highly dispersive and is described by an array of space harmonics. The high order harmonics are subject to a larger damping ratio than the low frequency harmonics due to higher losses which are dependent on skin effect and eddy currents.

The approach taken is to establish two fixed-parameters equivalent circuits: a low frequency (or dominant mode) model and a limiting high frequency model. The low frequency model uses measured component values or calculated parameters. The high frequency model uses parameter values, established from reflectometer measurements of a single magnet. The dominant model response is calculated using the former model; the high frequency response, using the latter model.

The equivalent circuit of the magnet is given in Figure 2 with parameter values listed in Table I. The reflectometers measurements are discussed in Appendix A.

TABLE I

PARAMETER VALUES OF EQUIVALENT CIRCUIT

PARAMETERS	DOMINANT MODE	HIGH FREQUENCY MODE
Frequency	4.9 Khz	416 Khz
L (per section)	3.2 mH	294 µH
C (per section)	.01µF	.005µF
R (per section)	12.6 x 10 ⁻³ Ω	.118Ω
Zo (surge impedance)	565 <u>n</u>	245 Ω
au (delay per sections)	5.6µsec	1.2µsec

Wave Response

The magnet wave response can be related to the response of a smooth loss-free, shortcircuited transmission line excited by a voltage step. The voltage and current response at the center of this line is given in Figure 3, where

V = magnitude of exciting voltage
Zo =
$$\sqrt{\frac{L}{C}}$$
 = surge impedance of line
 τ = N \sqrt{LC} = one way delay of line
N = length of line

Note that the average value of current increases with a slope given by

$$\frac{\mathrm{di}}{\mathrm{dt}} = \frac{\mathrm{V}}{\mathrm{Z}_{\mathrm{O}}} \frac{1}{\tau} = \frac{\mathrm{V}}{\mathrm{NL}}$$

At a time t following the application of the driving voltage, the ratio of the current wave propagating in the line (Δ i) to the average current in the line (i) is given by

$$\frac{\Delta i}{i} = \frac{N/LC}{t}$$

To reach a steady state or lumped constant response, the propagating wave is damped by the series loss element R. After traveling a distance d on the line, the propagating wave is damped to the value

$$\Delta i = V \sqrt{\frac{C}{L}} e^{-\alpha d}$$

where $\alpha = \frac{R}{2ZO}$ nepers/length = attentuation constant of line.

Thus,

$$\frac{\Delta i}{i} = \frac{N\sqrt{LC}}{t} e^{-\alpha d}$$

With the velocity of propagation ν given by

$$\nu = \frac{1}{\sqrt{LC}}$$

and the distance d traveled by the initial step, as

$$d = \frac{t}{\sqrt{LC}}$$

thus $\alpha d = \frac{R}{2L} t$

and $\frac{\Delta i}{i}$ is given by

 $\frac{N/LC}{t}$ e^{-2Lt}

Wave Damping

As a reasonable criterion for wave damping let $\frac{\Delta i}{i}$ be .01 at a time t of 1 milliseconds. Thus,

$$\frac{\Delta i}{i} = 50 \times 10^{-6}$$

at t equal to 2 milliseconds. This specification is based on the 8 millisecond restraint placed on the power supplies to change voltage from full invert to full rectify.

Using the limiting high frequency values from Table I, the value of R is calculated as

$$R = 0.453 \,\Omega$$

To damp the dominant mode the value of R is calculated as

$$\mathbf{R} = 14.72\,\mathbf{\Omega}$$

These damping calculations involve a series loss element.

The embodiment of the losses is through a shunt resistance R_D as is shown in Figure 4. The equivalence requires a shunt resistance of value

$$R_D = 4 K\Omega$$

for high frequency damping and

 $R_D = 659 \Omega$

for low frequency damping.

Thus by shunting a 3300 resistor across each half coil, the magnet wave is damped in a time of less than 2 milliseconds.

It is interesting to note that 659Ω is nearly the low frequency characteristic resistance of each section, resulting in a Qo (quality factor) of 1, and a system that is slightly under damped.

For an iterative structure, the current in the coil is not influenced by the value of the damping resistor.



Dipole Magnet String Test Magnet (#37) Now Shown

Figure 1



Figure 2

Single Frequency Equivalent Circuit of Dipole Magnet





Response at Center of Short Circuited Transmission Line



Figure 4

Shunt Loss Element WL_D > R_D

Appendix A

Reflectometer Measurement of Magnet

A fast voltage step was applied to the magnet through an adjustable resistor as is shown in Figure A-1.



Figure A-1

Reflectometer Test of Dipole Magnet

The source resistance R_g was adjusted to eliminate multipole reflections. The oscillogram in Figure A-2 gives the sending end and receiving end voltages for an open circuited line. The oscillogram in Figure A-3 gives the sending end voltage for a short circuited line. For both tests R_g was 2450. In Figure A-2 note that the initial sending end voltage is 1/2 the final value. In both oscillograms note the time delay of the reflection is approximately 2.4 μ sec. Thus, the values of Z_0 and τ are measured as

$$Z_0 = 2450$$

and

 $\tau = 1.2 \mu \text{sec}$

and are used to establish Table I.







• :

Response of Open Circuit Line



Response of Short Circuit Line