

GAUSS CLOCK CALIBRATION

H. Weisberg

March 1978

Collider Accelerator Department
Brookhaven National Laboratory

U.S. Department of Energy

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.EY-76-C-02-0016 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Accelerator Department
BROOKHAVEN NATIONAL LABORATORY
Associated Universities, Inc.
Upton, New York 11973

AGS DIVISION TECHNICAL NOTE

No. 145

GAUSS CLOCK CALIBRATION

H. Weisberg
March 13, 1978

The "gauss clock" consists of a voltage to frequency converter driven by the voltage picked up on a winding on the backleg of the E20 magnet. The gauss clock counts provides a number that is related to the main magnet field and therefore the proton momentum. The nominal calibration was set up to be

$$P \text{ (MeV/c)} = 0.5 G$$

where G is the gauss clock up-counts minus down-counts starting from reference time T_0 .

If the gauss clock is linear, it can be calibrated by measuring the frequency of the accelerating rf and the beam radius for various gauss clock readings during the acceleration cycle. Define the following quantities:

- m = proton mass = $938.2796 \text{ MeV}/c^2$
- c = velocity of light = $2.99792458 \times 10^{10} \text{ cm/sec}$
- r = average radial displacement of the beam with respect to the horizontal pick-up electrodes
- r_0 = radius of that equilibrium orbit for which $r = 0$
- f = rf frequency
- f_0 = frequency for a particle with velocity c on the equilibrium orbit of radius r_0
- h = harmonic number of the AGS = 12
- γ_{tr} = transition gamma
- P_0 = momentum of a proton that is on the equilibrium orbit of radius r_0 .

Then the rf frequency is given by

$$f = \frac{f_o}{\sqrt{1 + \frac{m^2}{P_o^2}}} \left[1 + \frac{r}{r_o} \left(\frac{\gamma_{tr}^2}{1 + \frac{P_o^2}{m^2}} - 1 \right) \right] \quad (1)$$

Now let us assume that the integrated gauss clock counts are linearly related to the equilibrium orbit momentum

$$P_o = G_1 (G + G_o) \quad (2)$$

Here G_1 and G_o are calibration constants to be determined; G_1 should be approximately 0.5 MeV/c per count and G_o is related to the field at time T_o . Since r_o is related to f_o by

$$r_o = \frac{h c}{2\pi f_o} \quad (3)$$

we can rewrite Eq. (1) as

$$f = \frac{f_o}{\sqrt{1 + \left[\frac{m}{G_1(G+G_o)} \right]^2}} \left\{ 1 + \frac{2\pi f_o r}{hc} \left[\frac{\gamma_{tr}^2}{1 + \left[\frac{G_1(G+G_o)}{m} \right]^2} - 1 \right] \right\} \quad (4)$$

A set of measurements of f , r and G at 27 different times during the acceleration cycle was made. The frequency f was measured with a Hewlett Packard 5345A 500 MHz time base digital frequency ratio counter. A gate time of 100 μ sec was used for momenta up to 4.5 GeV/c. From 4.5 to 9 GeV/c, where greater frequency accuracy was needed and the frequency was changing less rapidly, a 1 msec gate was used. Above 9 GeV/c a 10 msec gate was used. The gauss clock reading was always taken at a time later than the frequency meter "arm" pulse by an amount equal to one half the gate time, so that the effect of the frequency rise with time cancelled to first order.

The mean radius r was obtained from the average of the signals from the 46 pick-up electrodes that were available at the time of the measurement.

The frequency measurements were fit to Eq. (4) by non-linear least squares, treating f_0 , G_1 and G_0 as free parameters. To avoid magnet saturation effects, only data below 15 GeV/c were used. A constant value $\gamma_{tr}^2 \approx v_H^2 \approx 8.7^2$ was used. An uncertainty of ± 0.05 cm was assumed for each radius measurement. The results* were

$$f_0 = (4.457165 \pm 0.000015) \times 10^6 \text{ Hz}$$

$$G_1 = 0.50568 \pm 0.00016 \text{ MeV/c per count}$$

$$G_0 = 107.0 \pm 0.6 \text{ counts}$$

By Eq. (3), the measured value of f_0 gives $r_0 = 5057.43$ in., which agrees with the AGS nominal design radius of 5057.4 in.

We now have two different measurements of momentum: from the gauss clock by the equation

$$P = G_1 (G + G_0) \left(1 + \frac{r}{r_0} \gamma_{tr}^2\right) \quad (5)$$

and from the rf frequency by

$$P = \beta m \sqrt{1 - \beta^2} \quad \text{where} \quad \beta = (f/f_0) (1 + r/r_0) \quad (6)$$

Figure 1 gives the ratio of the momenta determined by these two methods for the various points measured. The fact that this ratio is equal to one to within a few tenths of a per cent below 15 GeV/c is a measure of the internal consistency of the measurement. Above 15 GeV/c, a systematic discrepancy sets in, reaching 1.5% at 28 GeV/c. Such an effect is expected from magnet saturation.

From the measurements we can work backward and apply a correction (including the magnet saturation effect) to quoted values of AGS momentum for recent operation:

<u>Nominal Momentum</u>	<u>Corrected Momentum</u>	
28.2 GeV/c	28.9 GeV/c	(Fast Extracted Beam)
28.2	29.0	(Slow Extracted Beam)

* The long term stability of the gauss clock has not been investigated. The quoted uncertainties correspond only to the internal consistency of the measurements at one time.

The FEB value is for a radius at extraction of $r = - 0.9$ cm, which corresponds to recent operating conditions. The SEB value is for $r = + 0.2$ cm, which corresponds to the radius at which $\nu = 8-2/3$ for recent settings of the ring quadrupoles.

HW/lsk

TO: Dept. Admin.
AD Physicists
AGS Div. Engineers
MCR
E. Gill
R. Warkentien
T. Wild

DATA OF 3/7/78
RATIO OF MOMENTUM FROM R.F. FREQUENCY TO MOMENTUM FROM GAUSS CLOCK
F0 = 4457.16540 KHZ; G1 = 0.50568 MEV/C PER COUNT; G0 = 107.0 COUNTS;
ERROR BARS CORRESPOND TO AN UNCERTAINTY IN RADIUS OF 0.050 CM.




Fig. 1