

BNL-104632-2014-TECH

AGS/AD/Tech Note No. 205;BNL-104632-2014-IR

NEUTRINO HORN WITH ECCENTRIC INNER CONDUCTOR

L. E. Repeta

August 1984

Collider Accelerator Department Brookhaven National Laboratory

U.S. Department of Energy

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.DE-AC02-76CH00016 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Accelerator Department BROOKHAVEN NATIONAL LABORATORY Associated Universities, Inc. Upton, New York 11973

AGS Division Technical Note No. 205

NEUTRINO HORN WITH ECCENTRIC INNER CONDUCTOR

L.E. Repeta

August 6, 1984

INTRODUCTION

A neutrino horn is basically a coaxial transmission line constructed of air filled concentric conducting cylinders or cones. Axial electric current flows on the inner diameter of the outer conductor. The front end is shortcircuited which enables the outside of the inner conductor to carry the return current in the opposite direction.

When the cylindrical axis of the inner and outer conductors are not coincident, see Figure I, the result is an unbalanced force on the inner conductor. Due to rapid pulsing of the neutrino horn this flexural force could produce an oscillation about the equilibrium position. This vibration, if of significant magnitude, could render the device dynamically unstable. The purpose of this note is to document the equation used to evaluate the force per unit length caused by conductor eccentricity.



NOTATION

P. d

W	STORED ENERGY IN THE MAGNETIC FIELD	JOULES
X	DISPLACEMENT	METERS
F	FORCE	NEWTONS; POUNDS
I	CURRENT	AMPERES
^Z c	CHARACTERISTIC IMPEDANCE	OHMS
L	INDUCTANCE/UNIT LENGTH	HENRY/CM
C	CAPACITANCE/UNIT LENGTH	FARAD/CM
v	VELOCITY OF LIGHT (3X10 ¹⁰)	CM/SECOND
ε	PERMITTIVITY (DIELECTRIC CONSTANT) 8.85x10 ⁻¹⁴	FARAD/CM
D	INNER DIAMETER OF THE OUTER CONDUCTOR	METERS
đ	OUTER DIAMETER OF THE INNER CONDUCTOR	METERS
L	LENGTH	CENTIMETER

2

MATHEMATICAL CONCEPT

Force can be defined by the partial differential equation

$$F = -\frac{\partial W}{\partial X}$$
(1)

The stored energy W in the magnetic field of a self-inductance L due to a current I flowing is

 $W = \frac{1}{2} L I^2$

Taking the partial derivative yields

$$\frac{\partial W}{\partial X} = \frac{1}{2} I^2 \frac{\partial L}{\partial X}$$

Substituting in equation (1) gives

$$\mathbf{F} = -\frac{1}{2} \mathbf{I}^2 \frac{\partial \mathbf{L}}{\partial \mathbf{X}}$$
(2)

The following argument is based on a method similar to the one developed by Brown,¹ based on an equation for the capacitance per unit length between two eccentric cylinders derived by Smythe.²

The characteristic impedance of a coaxial transmission line is

$$Z_{c} = \sqrt{\frac{L}{C}}$$
(3)

The velocity of a wave on the line is

$$v = \frac{1}{\sqrt{LC}}$$
(4)

The characteristic impedance is then

$$Z_{c} = \frac{1}{vC}$$
(5)

The equation for the capacitance per unit length (farads per centimeter) of an eccentric coaxial line derived by Smythe is, expressed in terms of radii,³

$$C = \frac{2\pi\varepsilon}{\cosh^{-1}\left(\frac{b^2 + a^2 - X^2}{2ba}\right)}$$
(6)

Let

$$U = (\frac{b^2 + a^2 - X^2}{2ba})$$

Then U expressed in terms of diameters is

$$U = \frac{1}{2} \left(\left(\frac{D}{d} \right) + \left(\frac{d}{D} \right) - \left(\frac{4x^2}{dD} \right) \right)$$

In simplified form equation (6) is

$$C = \frac{2\pi\varepsilon}{\cosh^{-1}U}$$
(7)

Substituting equation (7) in equation (5) yields

$$Z_{c} = \frac{1}{v} \cdot \frac{\cosh^{-1} U}{2\pi\varepsilon}$$
(8)

Solving equation (3) for L and substituting equation (8) yields an expression for the inductance per centimeter,

4

$$L = Z_{c}^{2} C = \left(\frac{1}{v} \cdot \frac{\cosh^{-1}U}{2\pi\varepsilon}\right)^{2} \left(\frac{2\pi\varepsilon}{\cosh^{-1}U}\right)$$
$$L = \frac{1}{v^{2}} \left(\frac{\cosh^{-1}U}{2\pi\varepsilon}\right) = \frac{1}{v} \left(60 \cosh^{-1}U\right)$$
$$L = 0.2 \times 10^{-8} \cosh^{-1}U$$
(9)

Let

,

$$k = 0.2 \times 10^{-8}$$

Then

$$L = k \cosh^{-1} U$$

$$\cosh\left(\frac{L}{k}\right) = U$$
(10)
$$\cosh\left(\frac{L}{k}\right) = \cosh(\psi) = U = f(X)$$

$$\frac{\partial}{\partial x} \cosh(\psi) = \sinh(\psi) \quad \frac{\partial \psi}{\partial X} = \frac{\partial}{\partial X} f(X)$$

$$\frac{1}{k} \sinh\left(\frac{L}{k}\right) \quad \frac{\partial L}{\partial X} = \frac{1}{2} \left(-\frac{8X}{dD}\right)$$

$$\frac{\partial L}{\partial X} = -\frac{4X}{dD} \cdot \frac{k}{\sinh\left(\frac{L}{k}\right)}$$
(11)

Knowing that

<u>9x</u> 9

,

$$\cosh^2 x - \sinh^2 x = 1$$

- -

6

Then

$$\sinh x = \sqrt{\cosh^2 x - 1}$$
$$\sinh \left(\frac{L}{k}\right) = \sqrt{\cosh^2 \left(\frac{L}{k}\right) - 1}$$

$$\cosh \left(\frac{L}{k}\right) = U$$

Then

٠

$$\sinh \left(\frac{L}{k}\right) = \sqrt{U^2 - 1}$$

Equation (11) becomes

$$\frac{\partial L}{\partial X} = -\frac{4X}{dD} \cdot \frac{k}{\sqrt{U^2 - 1}}$$

Substituting in equation (2) yields the force per centimeter length

$$\frac{F}{L} = -\frac{1}{2} I^{2} \left(-\frac{4X}{dD}\right) \left(\frac{k}{\sqrt{U^{2}-1}}\right)$$

$$\frac{F}{L} = \frac{0.4 \times 10^{-8} I^{2} X}{dD} \cdot \frac{1}{\sqrt{U^{2}-1}}$$
(12)

NUMERICAL ANALYSIS

Assume I = 30×10^4 amperes and equation (12) becomes

$$\frac{F}{\ell} = 360 \cdot \frac{X}{dD} \cdot \frac{1}{\sqrt{U^2 - 1}} \qquad (nt/cm)$$

Where

 $\mathbb{U} = \frac{1}{2} \left(\left(\frac{\mathrm{D}}{\mathrm{d}} \right) + \left(\frac{\mathrm{d}}{\mathrm{D}} \right) - \left(\frac{4\mathrm{x}^2}{\mathrm{d}\mathrm{D}} \right) \right)$

Using the above expressions for F/L and U, the values presented in Table I were calculated. The quantities X, d and D are expressed in meters.

X(M)	F/L d=0.019 D=0.064	F/L d=0.076 D=0.147	F/L d=0.127 D=0.203	F/L d=0.127 D=0.300
	04 020420	16 601088	7 020702	3 634527
0.00100	04.030420 7/ 770111	14.401088	6.256401	3,234700
0.00076	63,843030	10,944016	5.342445	2.762190
0.00063	52.913235	9.071726	4.428535	2.289693
0.00051	42.828841	7.343602	3.584962	1.853550
0.00038	31.908104	5.471593	2.671121	1.381069
0.00030	25.189280	4.319637	2.108770	1.090315
0.00020	16.792039	2.879733	1.405840	0.726875
0.00010	8.395775	1.439859	0.702918	0.363437
		TABLE I		

Converting the first two left hand columns to units of inches and pounds/inch we obtain,

X (inches)	F/& (#/in)	d=0.750 D=2.500
0.040	7.437	
0.035	6.618	
0.030	5.650	
0.025	4.683	
0.020	3.790	
0.015	2.824	
0.012	2.229	
0.008	1.486	
0.004	0.743	

7

CONCLUSIONS

From the computer printout (Table I) note that the slope within each geometric situation is constant (the function changes uniformly), therefore, written in point slope form we have

$$\frac{F}{\ell} = mX + b$$

where

$$m = SLOPE$$

Substituting in equation (12) X = 0, yields F/& = 0, therefore b = 0, and the above equation becomes

$$\frac{F}{\ell} = mX$$

For each geometric configuration we need only compute one case. Then substituting in the above slope equation, additional values of F/ for any given eccentricity can be computed.

The on-site machine shop practices enables them to maintain conductor straightness well within the 12 to 15 mil range. The smaller diameters, most critical situation, have larger wall thicknesses (a compressive pressure develops during pulsing) which makes it easier for the machine shop to maintain straightness. In addition, the inner conductor is assembled with a prescribed amount of tension in the axial direction. Small amounts of conductor eccentricity will not reduce the structural integrity of the neutrino horn.

ACKNOWLEDGEMENTS

Thanks to Ralph Sanders for his help and an enlightening dicussion. Thanks also to David Witkover for the computer program and printout.

FOOT NOTES

.....

- Brown, George H., "Impedance Determination of Eccentric Lines," <u>Electronics</u>, Vol. 15, 1942, p. 49.
- Smythe, William R., <u>Static and Dynamic Electricity</u>, McGraw-HIll Book Co., New York, Third Edition, 1968, pp. 76-78.
- 3. Ibid., Equation 5, p.78.

WPC

Distribution: A.D. S&P