



BNL-105796-2014-TECH

EP&S No. 80;BNL-105796-2014-IR

A Datacon-CAMAC module for the DIBBUK control system

R. Frankel

May 1976

Collider Accelerator Department
Brookhaven National Laboratory

U.S. Department of Energy

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.E(30-1)-16 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

DISCLAIMER

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

BROOKHAVEN NATIONAL LABORATORY
Associated Universities, Inc.
Upton, New York

EP&S DIVISION TECHNICAL NOTE
NO. 80

R. Frankel and D. I. Lowenstein

May 27, 1976

A DATACON-CAMAC MODULE FOR THE DIBBUK CONTROL SYSTEM

The DATACON-CAMAC unit provides secondary beam line information through the CAMAC Dataway to the experimenters computer. Each element, e.g. magnet power supply,¹ consists of two successive 16 bit words. There are a total of 64 words per module with the first element being words #0 and #1 and the rest in sequential order. The elements are loaded in the same order as is presented by the LIST task.² The module is loaded with updated values only when the MONITR task is active, i.e. once every five seconds when MONITR is running. All elements are updated even though they may not be a member of the current operation subset or be deferred. Should an element become deferred, a LAM is generated. The DATACON³ and CAMAC operations are asynchronous with respect to each other. The magnet power supply format is the following:

<u>WORD 1:</u>	Bits	0-7	=	Element DATACON Address
	Bit	8	=	Deferred by MONITR task
	Bits	9-12	=	0 = Shunt
				1 = 25 mV Calibration Reference
				2 = 75 mV Calibration Reference
				3-17 ₈ = Unused Presently
	Bit	13	=	1 = "A" Polarity
				0 = "B" Polarity
	Bit	14	=	1 = Rectifier On
				0 = Rectifier Off
	Bit	15	=	1 = Standby On
				0 = Standby Off

WORD 2 Bits 0-11 = Element Last Read Magnitude
 Bits 12-15 = Unused Presently

CAMAC Specifications

The CAMAC command functions are the following:

	<u>COMMAND</u>	<u>ACTION</u>
F(0)	- A(i) (i = 0-15)	Gates External "Group One" Data Onto Dataway (Words 0-15)
F(1)	- A(i) (i = 0-15)	Gates External "Group Two" Data Onto Dataway (Words 16-31)
F(2)	- A(i) (i = 0-15)	Gates External "Group Three" Data Onto Dataway (Words 32-47)
F(3)	- A(i) (i = 0-15)	Gates External "Group Four" Data Onto Dataway (Words 48-63)
F(8)	- A(0)	Returns Q if LAM is set.
F(10)	- A(0) - S1	Clear LAM
F(24)	- A(0) - S1	Disable LAM
F(26)	- A(0) - S1	Enable LAM
C - S2		Clears LAM
Z - S2		Clears LAM - Disable LAM

Status Indications

The front panel status indications are the following:

N light flashes whenever module is addressed by CAMAC.

LE light on whenever LAM is enabled.

L light on whenever a LAM is pending.

DR light flashes whenever accepting DATACON data.

DATACON Specifications

All transmissions must have the SET/READ bit enabled. A LAM is generated with bit C6.¹ The CAMAC module address may be adusted via slide switches to any address between 0-377₈.

C5 - C0	Memory Address (0 - 77 ₈)
C6	LAM Set Flag
M15 - M0	Magnitude

References:

1. V. J. Kovarik, BNL, EP&S Tech. Note #58 (1973).
B. B. Culwick, BNL, CAOS Hardware Note APSC-B (1975).
2. D. I. Lowenstein, BNL, EP&S Tech. Note #75 (1975).
D. I. Lowenstein, F. W. Stubblefield, Nucl. Instr. & Mthds.,
129, 575 (1975).
3. R. Frankel, BNL, AGS Tech. Note #88 (1971).
V. J. Kovarik, BNL, EP&S Tech. Note #49 (1972).
B. B. Culwick, BNL, EP&S Tech. Note #50 (1972).
V. J. Kovarik, BNL, EP&S Tech. Note #58 (1973).

RF/DIL:as

Distr.: Dept. Adm.
Dept. S&P
Experimenters