



Brookhaven  
National Laboratory

BNL-103987-2014-TECH

AGS.SN109;BNL-103987-2014-IR

## Longitudinal Impedance Measurements II

F. Pedersen

April 1978

Collider Accelerator Department  
**Brookhaven National Laboratory**

**U.S. Department of Energy**

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.EY-76-C-02-0016 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

## **DISCLAIMER**

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Date 4/6/78 Time 800-1500 Experimenters F. Pedersen, E. Raka, E. Gill

Subject Longitudinal Impedance Measurements II

---

OBSERVATIONS AND CONCLUSION

Introduction:

As in the previous run the goal was to drive some of the potentially unstable coupled bunch resonant modes in the neighborhood of  $h = 12$ . Exciting both dipole and quadrupole oscillations and measuring accurately their frequencies along with a determination of the unperturbed bunch length will then permit a calculation of the imaginary part of the coupling impedance at a given energy.

Procedure:

The intensity was reduced to  $\approx 2.5 \times 10^{12}$  and transition adjusted for no phase space dilution. Then a 1 sec. flat top was added to the magnet cycle and fast extraction set up at the end of this time. Next the frequency synchronization loop was closed on the flat top and it functioned perfectly. That is the beam frequency was synchronized to a stable external oscillator at 4,454,861 C.P.S. in a phase lock loop. Then a small amount of rf excitation was added to the 9 accelerating stations at the 13th and 14th harmonics  $\pm$  the phase oscillation frequency and twice the phase oscillation frequency ( $\approx 180, 360$  C.P.S.). The E-20 WBPU was fed to the HP spectrum analyser which was tuned to  $\approx$  the exciting frequency with bandwidths 30-300 cycles (no sweep). One then looked for a growing amplitude of one of these lines during the .2-.3 second period of the rf excitation. Fine tuning of the excitation frequency in step of 1 or 2 cycles/sec. permitted accurate determination of the resonant frequency of a given mode.

Observations:

Considerable time was lost adjusting the radial control loop to carry the beam through the flat top and to set up the fast extracted beam, so data was taken only during the last 90 minutes of the run.

Excitation of the dipole mode at the upper and lower sideband of the 13th harmonic yielded a clean reproducible linear growth of the resonances. The upper sideband or  $n = 1$  coupled bunch mode exhibited a slow exponential additional growth after the excitation was removed while the lower sideband or  $n = 11$  mode decayed in the expected manner when the excitation was removed.

Similar growth was observed when the quadrupole mode was driven at  $h = 13$  but both signal decayed after the excitation was removed. This is not understood since it was expected that the quadrupole mode for the upper sideband would also be unstable. Finally the dipole mode sidebands at  $h = 14$  were driven but this time the rate

of growth during excitation was not linear. A fast initial rise was followed by a rapid decrease in slope which continued to decay with time. After removal of the excitation the upper sideband actually exhibited a slight decay while the lower sideband showed a slight growth. This again is a result that needs further investigation.

Results:

In any event a very accurate measurement of the coherent dipole frequency was obtained;  $178.5 \pm .5$  C.P.S., from both  $h = 13$  and  $14$  excitation. The quadrupole frequency from the  $h = 13$  excitation was  $35116 \pm .7$  so that  $\Delta f$  the incoherent dipole frequency shift is  $2 |f_q - 2f_d|$  or  $10.8$  C.P.S. This along with the  $\tilde{\nu}$  bunch length of  $19$  nsec and a  $V_{rf} = 262$  Kv as determined from the beam energy and  $f_d$  results in a  $Z/n \tilde{\nu} \approx 36 \Omega$  inductive at  $27.4$  GeV.