



BNL-104461-2014-TECH

AGS/AD/Tech Note No. 20;BNL-104461-2014-IR

## SUPPRESSION OF VERTICAL COHERENCE IN THE AGS

E. C. Raka

April 1966

Collider Accelerator Department  
**Brookhaven National Laboratory**

**U.S. Department of Energy**

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No. AT-30-2-GEN-16 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

## **DISCLAIMER**

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Accelerator Department  
BROOKHAVEN NATIONAL LABORATORY  
Associated Universities, Inc.  
Upton, L.I., N.Y.

AGS DIVISION TECHNICAL NOTE

No. 20

E.C. Raka

April 18, 1966

SUPPRESSION OF VERTICAL COHERENCE IN THE AGS

Recent investigations have revealed a simple method for suppressing the early vertical coherence when it appears. As in the case of the high energy occurrence of this phenomena (when  $dv_v/dr$  passes through zero) it can be suppressed by programming the vertical sextupole. This increases the spread in the quantity  $(n-v_v)\omega_0$  and permits Landau damping to predominate.

At present the vertical sextupoles can be programmed from zero to seven amperes in about 40 milliseconds. This produces a 50% increase in  $dv_v/dr$  at 73 milliseconds and is close to the limit of the sextupole power supply. Currents much higher than this at this time in the acceleration cycle can produce beam loss since it is in this region that the horizontal half integral resonance is crossed. Thus, this method of coherence suppression has definite limitations.

However, during recent operation when for one reason or another the vacuum has been poor so that early coherence as large as .7cm peak to peak was present a program starting at 50 milliseconds and stopping at 150 milliseconds completely suppressed the oscillations. The beam intensity was as high as  $1.3 \times 10^{12}$  and the I-10 vacuum  $> 10^{-5}$  mm.

It should be noted that the beam position during this time was on the inside as given by the radial error signal i.e.,  $> +1$  volt. Past measurements indicate that the coherence threshold is lowered if one operates further outside i.e., near zero on the radial error signal though the reason for this is not yet understood. Fortunately, the inside position gives higher intensity and hence is the normal operating point.

Because of the above mentioned limitations on using the vertical sextupoles to suppress the early coherence it is felt that in the near future as the AGS intensity is increased a feedback stabilization system will be needed. Since only a pure  $n=9$  mode has been observed early, the system need not accommodate higher order modes nor must it act on the bunches individually. However, it shall have to operate over a range in  $\nu_v$  from 8.90 to 8.75 and in  $f_o$  from 240 to 372 kc. A bandwidth of 20kc to 100kc will cover this range satisfactorily but one will, of course, have to provide a  $90^\circ$  phase shift over this spectrum.

A future report will discuss the vertical instability in detail and a separate design study of a damping system is also planned.

Distribution: AGS Division Staff  
E.C. Courant  
M.Q. Barton  
D.S. Robertson  
J.G. Cottingham

ECR/pam