



BNL-104510-2014-TECH

AGS/AD/Tech Note No. 77;BNL-104510-2014-IR

# VOLTAGE RIPPLE ON SLOW BEAM EXTRACTION EQUIPMENT

J. G. Cottingham

March 1970

Collider Accelerator Department  
**Brookhaven National Laboratory**

**U.S. Department of Energy**

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No.AT(30-1)-16 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

## **DISCLAIMER**

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

Accelerator Department  
BROOKHAVEN NATIONAL LABORATORY  
Associated Universities, Inc.  
Upton, New York

AGS DIVISION TECHNICAL NOTE

No. 77

J.G. Cottingham  
March 25, 1970

VOLTAGE RIPPLE ON SLOW BEAM EXTRACTION EQUIPMENT

The present slow external beam from the AGS is modulated due to ripple voltage in the power system that drives the extraction magnet elements as well as ripple in the main magnet system. In order to reduce this ripple structure, filtering must be added to certain power systems. The limits on voltage ripple may be estimated as follows.

If we assume the beam is uniformly populated in  $v$  and occupies a region  $0.2 v$  units wide, then the rate of beam spill will be proportional to  $\frac{dv}{dt}$ . This assumption of uniform population is a gross simplification, but the results will still serve as a useful guide in equipment design.

Each magnet element is assumed to be a simple L and R in series. The driving generator consists of a dc battery ( $E_0$ ) and a ripple generator ( $\Delta e$ ) in series.

$$\Delta i = \frac{\Delta e}{z} \approx \frac{\Delta e}{\omega L}$$

Note  $E_0 = I_0 R$

$$\therefore \frac{\Delta i}{I_0} = \frac{\Delta e}{\omega L} \cdot \frac{R}{E_0} = \frac{\Delta e}{E_0} \cdot \frac{1}{\omega \lambda} \quad \text{or} \quad \frac{\Delta e}{E} = \frac{\Delta i}{I_0} \omega \lambda$$

where  $\lambda$  is the time constant  $\frac{L}{R}$

if  $v = \alpha t + \beta \sin \omega t$  where  $\alpha = \frac{0.2}{\text{flat top time}}$

$$\frac{dv}{dt} = \alpha + \beta \omega \cos \omega t.$$

Since the spill is proportional to  $\frac{d\psi}{dt}$ , the fractional spill ripple  $f = \frac{2\beta\omega}{\alpha}$  measured as a ratio of peak to peak spill ripple to the average spill.

$\beta$  is measured in  $\psi$  units to obtain  $\Delta i$  we need only divide by the appropriate co-efficient  $\gamma$  ( $\psi$  units per amp)

$$\therefore \Delta i = \frac{\beta}{\gamma} = \frac{f\alpha}{2\omega\gamma}$$

$$\text{and } \frac{\Delta e}{E} = \frac{f\alpha\omega\lambda}{2\omega\gamma I_0} = \frac{f\alpha\lambda}{2\gamma I_0}$$

The following table evaluates this expression for the magnet elements indicated.

| Element               | Time Constant | Allowed Spill Ripple (f) | $\frac{\Delta e}{E}$ | $\frac{\Delta e}{E}$ |
|-----------------------|---------------|--------------------------|----------------------|----------------------|
|                       |               |                          | 400 msec Flat Top    | 1 sec Flat Top       |
| Backleg Windings      | .083          | 10%                      | 10.4%                | 4.2%                 |
| Quadrupole Horizontal | .150          | 20%                      | 7.5%                 | 3.0%                 |
| Quadrupole Vertical   | .150          | 10%                      | 7.5%                 | 3.0%                 |
| Magnet Voltage*       |               | 20%                      | 0.7%                 | 0.3%                 |

\* Extracted from AGSCD Technical Note #1, June 28, 1965.

The spill ripple due to ripple in the sextupole magnets are being studied by others and will be reported later.

Distr: Department Administration  
AGS Division Staff