

# The Effect Of Landau Damping On The Longitudinal Phase Space Instability Across the Transition Energy

S. Y. Lee

March 1984

Collider Accelerator Department  
**Brookhaven National Laboratory**

**U.S. Department of Energy**

USDOE Office of Science (SC)

Notice: This technical note has been authored by employees of Brookhaven Science Associates, LLC under Contract No. DE-AC02-76CH00016 with the U.S. Department of Energy. The publisher by accepting the technical note for publication acknowledges that the United States Government retains a non-exclusive, paid-up, irrevocable, world-wide license to publish or reproduce the published form of this technical note, or allow others to do so, for United States Government purposes.

## **DISCLAIMER**

This report was prepared as an account of work sponsored by an agency of the United States Government. Neither the United States Government nor any agency thereof, nor any of their employees, nor any of their contractors, subcontractors, or their employees, makes any warranty, express or implied, or assumes any legal liability or responsibility for the accuracy, completeness, or any third party's use or the results of such use of any information, apparatus, product, or process disclosed, or represents that its use would not infringe privately owned rights. Reference herein to any specific commercial product, process, or service by trade name, trademark, manufacturer, or otherwise, does not necessarily constitute or imply its endorsement, recommendation, or favoring by the United States Government or any agency thereof or its contractors or subcontractors. The views and opinions of authors expressed herein do not necessarily state or reflect those of the United States Government or any agency thereof.

THE EFFECT OF LANDAU DAMPING ON THE  
LONGITUDINAL PHASE SPACE INSTABILITY ACROSS  
THE TRANSITION ENERGY

S. Y. Lee

Brookhaven National Laboratory

March 10, 1984

As pointed out by J.M. Wang (RHIC-PG32) that the microwave ~~in~~coherent instability may play an important role in the design of RHIC machine across the transition energy region. In this note we shall examine the growth rate in the presence of the beam momentum and energy spread. We shall proceed in three sections:

(I) The equation of longitudinal motion across the transition region and derive an invariant of the longitudinal phase space

(II) Discuss the dispersion integral of the instability.

(III) Conclusion and Recommendation.

# I Equation of Synchrotron motion near transition energy. 2

$$\theta = \varphi - \varphi_s$$

$$(h \Delta\omega) \Rightarrow \dot{\theta} \equiv \frac{h \eta \omega_0^2}{E \beta^2} W \quad W = \frac{\Delta E}{\omega_0}$$

$$\dot{W} = \frac{eV}{2\pi} (\Delta \sin \varphi - \Delta \sin \varphi_s) \approx \left( \frac{eV}{2\pi} \cos \varphi_s \right) \theta$$

$$H = \frac{h \eta \omega_0^2}{2pR} W^2 + \frac{eV}{2\pi} [\cos \varphi - \cos \varphi_s + (\varphi - \varphi_s) \Delta \sin \varphi_s]$$

$$\frac{d}{dt} \left( \frac{1}{\Omega_s^2} \dot{\theta} \right) + \theta = 0$$

$$\omega_w = \frac{c}{R} = \frac{\omega_0}{\beta}$$

$$\Omega_s^2(t) = \frac{\omega_0^2 h}{E(t)} \frac{eV}{2\pi} |\eta(t) \cos \varphi_s|$$

$$= \frac{\omega_0^2 h}{E_0} \frac{eV}{2\pi} |\cos \varphi_s| \left| \frac{2\dot{\gamma}}{\gamma^4} t \right| \equiv \frac{t}{T^3} \quad |t| \ll T = \frac{\delta E}{\dot{\gamma}}$$

$$\eta(t) \equiv \frac{1}{\gamma^2} - \frac{1}{\delta^2} \sim + \frac{2\dot{\gamma}}{\gamma^3} t$$

Assumptions

(i) Acceleration is an adiabatic process

$\gamma(t)$ ;  $\eta(t)$  is a smooth function of  $t$

$$\gamma(t) = \gamma_t + \dot{\gamma} t$$

$$T^3 = 2h \frac{\omega_w^2 eV \dot{\gamma}}{2\pi E_0 \gamma_t^4} |\cos \varphi_s|$$

$$\frac{d}{dt} \left( \frac{1}{\Omega_s^2 t^3} \dot{\theta} \right) + \theta = 0$$

$$t > 0 \quad y = \int_0^t dt' \Omega_s(t') = \frac{2}{3} \left( \frac{t}{T} \right)^{3/2}$$

$$\theta = y^{2/3} \Phi \quad x \equiv t/T$$

$$\frac{d^2 \Phi}{dy^2} + \frac{1}{y} \frac{d\Phi}{dy} + \left[ 1 - \frac{\left( \frac{2}{3} \right)^2}{y^2} \right] \Phi = 0$$

$$\theta = a x \left[ \cos \psi J_{2/3}(y) + \sin \psi N_{2/3}(y) \right]$$

$$\boxed{\frac{\theta}{xa} = \cos \psi J_{2/3}(y) + \sin \psi N_{2/3}(y)}$$

$$\frac{\hbar \eta \omega_0^2}{E \beta^2} W = \dot{\theta} = \frac{\theta}{Tx} + \frac{x^{3/2}}{T} a \left[ \cos \psi \left( \frac{2}{3y} J_{2/3} - J_{5/3} \right) + \sin \psi \left( \frac{2}{3y} N_{2/3} - N_{5/3} \right) \right]$$

$$\frac{1}{ax^{3/2}} \left( \frac{2\theta}{x} - \frac{\hbar T \eta \omega_0^2}{E \beta^2} W \right) = \cos \psi J_{5/3}(y) + \sin \psi N_{5/3}(y)$$

$$\begin{pmatrix} \cos \psi \\ \sin \psi \end{pmatrix} = M^{-1} \begin{pmatrix} \theta/xa \\ \left[ \frac{2\theta}{x} - \frac{\hbar T \eta \omega_0^2}{E \beta^2} W \right] / x^{3/2} a \end{pmatrix}$$

$$M \equiv \begin{pmatrix} J_{2/3} & N_{2/3} \\ J_{5/3} & N_{5/3} \end{pmatrix}$$

$$\cos^2 \psi + \sin^2 \psi = 1 \equiv \alpha_{\theta\theta} \theta^2 + 2\alpha_{\theta W} \theta W + \alpha_{WW} W^2 = \text{invariant}$$

$$\alpha_{\theta\theta} = \left[ \left( \frac{3}{2} \gamma N_{5/3} - 2N_{2/3} \right)^2 + \left( 2J_{2/3} - 1.5 \gamma J_{5/3} \right)^2 \right] / a^2 (\det)^2 \times^5$$

$$\alpha_{\theta W} = \frac{h T \eta \omega_0^2}{a^2 (\det)^2 \times E \beta^2} \left[ N_{2/3} \left( \frac{3}{2} \gamma N_{5/3} - 2N_{2/3} \right) - J_{2/3} \left[ 2J_{2/3} - \frac{3}{2} \gamma J_{5/3} \right] \right]$$

$$\alpha_{WW} = \frac{h^2 T^2 \eta^2 \omega_0^4}{a^2 (\det)^2 \times E^3 \beta^2} \left[ J_{2/3}^2 + N_{2/3}^2 \right]$$

Asymptotically:

$$\alpha_{\theta\theta} = 1 / \hat{\theta}^2 \quad \hat{\theta} = \left( \frac{2 A h^2 \omega_0^2 \gamma T^2}{\pi \epsilon_0 \beta^2 \gamma_t^4} \right)^{1/2} \left( \frac{t}{T} \right)^{1/4}$$

$$\alpha_{WW} = 1 / \hat{W}^2 \quad \hat{W} = \frac{1}{h} \left( \frac{A \epsilon_0 \beta^2 \gamma_t^4}{2 \pi h^2 \omega_0^2 \gamma T^2} \right)^{1/2} \left( \frac{T}{t} \right)^{1/4}$$

$$a^2 = \frac{2 A h^2 \omega_0^2 \gamma T^2}{3 \epsilon_0 \beta^2 \gamma_t^4}$$

$$[A] \equiv \text{eV sec.}$$

Gaussian Bunch.

$$\xi_0 \approx \sqrt{3}$$

$$\rho(\theta, W) = N \frac{\xi_0^2 [\alpha_{\theta\theta} \alpha_{WW} - \alpha_{\theta W}^2]^{1/2}}{\pi} e^{-\xi_0^2 (\alpha_{\theta\theta} \theta^2 + 2 \alpha_{\theta W} \theta W + \alpha_{WW} W^2)}$$

$$= N g(\theta) g(W)$$

$$g(W) = \frac{\xi_0 \sqrt{\alpha_{WW}}}{\sqrt{\pi}} e^{-\xi_0^2 \alpha_{WW} \left( W + \frac{\alpha_{\theta W}}{\alpha_{WW}} \theta \right)^2}$$

$$g(\theta) = \frac{\xi_0}{\sqrt{\pi}} \left[ \frac{\alpha_{\theta\theta} \alpha_{WW} - \alpha_{\theta W}^2}{\alpha_{\theta W}} \right]^{1/2} e^{-\xi_0^2 \left[ \frac{\alpha_{\theta\theta} \alpha_{WW} - \alpha_{\theta W}^2}{\alpha_{\theta W}} \right] \theta^2}$$

## II Coherent Instability.

5

a Coasting beam.

Small perturbation in current  $I = I_0 + I_1 e^{i n [(\theta - \Delta \Omega t) - \omega t]}$

$$\rightarrow \omega = \omega_0 + \omega_1 e^{i n [(\theta - \Delta \Omega t) - \omega t]}$$

$$\Rightarrow \text{Voltage change / turn} = - I_1 Z e^{i n [(\theta - \Delta \Omega t) - \omega_0 t]}$$

$$\frac{\partial E}{\partial t} = - \frac{\partial E}{\partial \theta} \omega + e U_s \frac{\omega}{2\pi}$$

$$\Rightarrow \frac{\partial \omega}{\partial t} = - \frac{\partial \omega}{\partial \theta} \omega - \frac{\partial \omega}{\partial E} \frac{\partial E}{\partial t} = - \frac{\partial \omega}{\partial \theta} \omega_0 + \frac{e \eta \omega_0^2 Z}{\beta^2 E \cdot 2\pi} I_1 e^{i n (\theta - \omega_0 t)}$$

$$\omega_1 \Delta \Omega = i e \eta \omega_0^2 I_1 \left( \frac{Z}{n} \right) / 2\pi \beta^2 E$$

Equation of continuity:  $\frac{\partial I}{\partial t} = - \frac{\partial I}{\partial \theta} \omega_0 - \frac{\partial \omega}{\partial \theta} I_0$

$$I_1 \Delta \Omega = \omega_1 I_0$$

$$\Delta \Omega^2 = i \frac{e \eta \omega_0^2 I_0}{2\pi \beta^2 E} \left( \frac{Z}{n} \right)$$

$$e^{-i n \Delta \Omega t}$$

$$: \begin{cases} \Delta \Omega_i > 0 & \text{unstable} \\ \Delta \Omega_i < 0 & \text{stable.} \end{cases}$$

$$\text{Growth} = e^{\int n \Delta \Omega_i dt}$$

high energy spread

$$1 = - \Delta \Omega^2 \int \frac{g'(\omega)}{\delta \Omega - \omega} d\omega$$



b Bunched Beam with energy spread [Wang - Pellegrini]

$$1 = -(\Delta\Omega)^2 \int \frac{\left(\frac{dg}{d\omega}\right)}{(\delta\Omega - \omega)} \cdot d\omega$$

normal modes  
 $\leftrightarrow$  (TDA RPA equations)  
 (phonon)

$$\int g \, d\omega = 1$$

$$\Delta\Omega^2 = i \frac{e^2 \eta \omega_0^2 I_{peak}}{2\pi \beta^2 E} \left(\frac{Z}{n}\right)$$

$$\propto \left[ \frac{\left(\frac{N}{B}\right) \cdot e^2}{A} \right]$$

$$= i \frac{e^2 \eta \omega_0^3 N}{(2\pi)^2 \beta^2 E} G(\theta) \left(\frac{Z}{n}\right)$$

see p. 4

$$\zeta \equiv \frac{Z}{n} = \zeta_r + i \zeta_i$$

$$\langle n \rangle = \frac{R}{b} \approx 2.0 \times 10^4 \quad (\text{RHIC})$$

RHIC-28

	P,	<sup>2</sup> H	C	S	Cu	I	Au
$\frac{N}{B} [10^9]$	$10^3$	$10^2$	22	64	4.5	2.6	1.1
e	1	1	6	16	29	53	79
A	1	2	12	32	63	127	197

$$\frac{Z}{n} = 2 + 5 \times 10^{-4}$$

50	66	51.2	60.1	57.5	34.8
			3.8		3.4

Growth

### III Conclusions and Recommendation

From the following table and figure, the following

conclusions can be drawn:

(1) less instability for higher harmonic number  $h$

(2) The phase space area should be at least

0.4 evsec/amu before the transition.

(3) Calculation indicates that there is an interesting correlation between the total growth

$$G = e^{\int \Omega_i dt} \quad (\Omega_i > 0)$$

and the parameters  $\left| \frac{Z}{n} \right| * N_B$ .

$^{197}_{79}\text{Au}$

$\gamma_T = 26.4$

$\langle n \rangle = 2,034 \times 10^4$

$V = 1.1 \text{ MV}$

$\bar{\beta} = 29.5 \text{ m}$

$\phi_s = 5.45^\circ$

$\bar{x}_p = 1.0$

$\dot{\gamma} = 3.2 \text{ /sec}$

$R = 610,168 \text{ m}, a = 0.03 \text{ m [tube radius]}$

$A_0$ [evsec]	H	$Re$ [ $\frac{Z}{n}$ ]	$N_B$ [ $10^9$ ]	$G = e^{\int \Omega_i dt}$	$ \frac{Z}{n}  \times N_B$
0.2	12x57	0	1.15	1.17	1.38
		5	4.15	19.7	5.91
		1	1.15	1.29	1.80
			2.30	3.05	3.59
		3	0.58	1.29	1.87
			1.15	2.97	3.72
			2.30	162	7.43
	6x57	1	1.15	1.42	
			2.30	4.59	
		3	0.58	1.39	
		1.15	4.05		
		2.30	6.92		
	5	1.15	43.76		
0.4	12x57	5	1.15	1.56	
			2.30	6.88	
	6x57	5	1.15	1.75	
			2.30	11.63	
0.4	12x57	5	4.5	2.91	

$^{63}_{29}\text{Cu}$

